

DMAT Sports Controller Specifications

Power 90 VAC to 265 VAC adapter supplied with IEC connector

Size (L" x W" x H")
12 3/4" x 8" x 1 3/4" (front)
3 5/8" (rear)
8 5/8" high to top of display

Weight 10 lbs

Rear Panel Connectors

VTR1,2,3,4,5,6	(All DB9F)
GPI	(DBF26F)
Power	(DB9M)
SHOTBOX	(DB9F)
PBIO	(DB9F)
Keyboard	(6-pin mini DIN)
Ref. Video In	(BNC)
Ground	Threaded stud

Display Easy to read, back-lit LCD display

Jog/Shuttle Wheel

With mechanical detents

RS422 Serial Connector

9-Pin D-Type, Female (DB9F)

Pin #	Function	Pin #	Function
1	Frame Ground	6	Receive Common
2	Receive A ⇐	7	Receive B ⇐
3	Transmit B ⇒	8	Transmit A ⇒
4	Transmit Common	9	Frame Ground
5	Spare		

Power Connector

9-Pin D-Type, Female (DB9M)

Pin #	Function	Pin #	Function
1	+5 vDC	6	+5 vDC
2	+5 vD C	7	Ground
3	Ground	8	Ground
4	+12 vDC	9	Ground
5	-12 vDC		

GPI IN/OUT CONNECTOR

26-Pin D-Type, Female (DB26F)

FOR **Abekas Mira**: THE **DMAT-AB** SPORTS CONTROLLER

KEY FEATURES:

"Elvis-like" functionality allows you to quickly mark, save and recall clips for instant replays with minimal keystrokes

"Instant Live Cut" switching between record streams

Clip from up to three record streams or from pre-loaded media

Instantly build and playout highlight lists, assigning playout speed to each element

Personalize control settings to operator's preference

Supports 400 clips and 20 playlists of 60 elements each

Fast, easy, precise and reliable control!

A WINNING COMBINATION:

The DMAT / Mira combination provides the fast, easy, precise and reliable control required in the demanding, unpredictable world of live sports. Instant replays, highlight packages and even pre-loaded media are never more than a few keystrokes away!

Unique to the DMAT / Mira pairing is the "Instant Live Cut" feature, allowing instant switching between the three record streams. This amazing feature provides the functionality of a six-channel video server and downstream cuts-only switcher—all within the cost-effective four-channel Mira / DMAT combination!

Ask your DNF Controls representative for more information or see us online at www.dnfcontrols.com.

DNF
C O N T R O L S

(818) 898-3380 - sales@dnfcontrols.com